

	Type	SPC 4320.320	SPC 5330.320	SPC 5350.320	SPC 6330.320	SPC 6350.320
Panel details	Supported Zones max.	32	128	128	512	512
	Zones on PCB	8	8	16	8	16
	Supported Outputs max.	30	128	128	512	512
	Outputs on PCB	6	6	12	6	12
	Areas	4	16	16	60	60
	Calendars	4	32	32	64	64
	Triggers	8	256	256	1024	1024
	Mapping Gates	4	128	128	512	512
	Log Intrusion	1.000	10.000	10.000	10.000	10.000
	Log Access	1.000	10.000	10.000	10.000	10.000
	Panel PSU available output	750 mA	750 mA	2.2 A	750 mA	2.2A
	Supported Active languages / System	EN + 4	EN + 4	EN + 4	EN + 4	EN + 4
	Supported battery capacity	7Ah	17Ah	2 x 27Ah	17Ah	2 x 27Ah
	Metal Housing size BxHxT mm	G2	G3	G5	G3	G5
User details	Users	100	500	500	2500	2500
	Paces	32	250	250	250	250
	Access Cards	100	500	500	2500	2500
	Web passwords	32	50	50	100	100
	User Profiles	100	100	100	100	100
	RS232	1	2	2	2	2
Connectivity	USB	1	1	1	1	1
	Ethernet	1	1	1	1	1
	Fast Programmer	1	1	1	1	1
X-Bus	X-Bus interface	1	2	2	2	2
	X-Bus devices max.	11	48	48	128	128
	X-Bus Keypads	4	16	16	32	32
	X-Bus I/O devices	5	16	16	64	64
	X-Bus Output devices	5	16	16	64	64
	X-Bus door expanders	2	8	8	32	32
Access Control	Doors only Entry	4	16	16	64	64
	Doors Entry / Exit	2	8	8	32	32
	Card readers max.	4	16	16	64	64
Transmission	IP dialer EDP / FlexC	on board	on board	on board	on board	on board
	Internal modems max.	2	2	2	2	2
	PSTN modems max.	1 + 1	1 + 1	1 + 1	1 + 1	1 + 1
Wireless	GSM modems max.	1 + 1	1 + 1	1 + 1	1 + 1	1 + 1
	Wireless Gateways	5+KP+P	16+KP+P	16+KP+P	64+KP+P	64+KP+P
	Wireless devices max.	32	120	120	120	120
	FOBs max.	32	50	50	100	100
Alarm verification	Emergency buttons max. MDT	32	128	128	128	128
	Verification zones	4	16	16	32	32
	IP cameras	4	4	4	4	4
	X-BUS Audio expanders max. SPC340 / SPC341 / SPCV440	4	8	8	16	16
	Audio Satellites max. 3 per X-BUS Audio expander	12	24	24	48	48
	E-Bus Gateway	5	5	5	5	5
E-Bus integration FW 3.6.6	Max no. of E-Bus SMT/SAT12/24 (recognized as 8 IN/2OUT)	4	15	14	63	62
	E-BUS SMT /SATdevices zones	16 (4xSxT12)	60 (15xSAT12)	56 (14xSxT12)	252 (63xSxT12)	248 (62xSxT12)
	Max no. of E-Bus PDM-E (recognized as 8 IN/2OUT)	4	15	14	56	56
	E-Bus PDM-E detectors zones	8 (PDM-E)	30 (PDM-E)	30 (PDM-E)	112 (PDM-E)	112 (PDM-E)
	E-Bus Keypads (*1)	4	16	16	16	16
	E-Bus PSUs (*2)	5	16	16	16	16
	E-Bus SMT44 (recognized as SPCE452)	4	4	4	4	4
E-Bus integration FW 3.7.1 and higher	E-Bus Gateway	5	5	5	5	5
	Max no. of E-Bus SMT/SAT12/24 (recognized as 8 IN/2OUT)	4	15	14	63	62
	E-BUS SMT /SATdevices zones	16 (4xSxT12)	60 (15xSAT12)	56 (14xSxT12)	252 (63xSxT12)	248 (62xSxT12)
	Max no. of E-Bus PDM-E (recognized as 2 IN/2OUT)	16	56	56	56	56
	E-Bus PDM-E detectors zones	32 (PDM-E)	112 (PDM-E)	112 (PDM-E)	112 (PDM-E)	112 (PDM-E)
	E-Bus Keypads (*1)	4	16	16	16	16
	E-Bus PSUs (*2)	5	16	16	16	16
E-Bus SMT44 (recognized as SPCE452)	4	4	4	4	4	

Supported E-Bus keypads  
 (\*1) SAK41/SAK51

Simulation of E-Bus devices  
 (\*2) SAP14/20 + SMT12 -> SPCP355 + SPCE652  
 SAP25 + 8 inputs -> SPCP355 + 2 X SPCE652